

(19) World Intellectual Property Organization
International Bureau



(43) International Publication Date
28 March 2002 (28.03.2002)

PCT

(10) International Publication Number
WO 02/25700 A2

(51) International Patent Classification⁷: H01L

(21) International Application Number: PCT/GB01/04211

(22) International Filing Date:
20 September 2001 (20.09.2001)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:
60/234,219 21 September 2000 (21.09.2000) US

(71) Applicant: CAMBRIDGE SEMICONDUCTOR LIMITED [GB/GB]; University Challenge Fund, 16 Mill Lane, Cambridge CB2 1SB (GB).

(72) Inventors: UDREA, Florin; 95 Burnside, Cambridge CB1 3PA (GB). AMARATUNGA, Gehan, Anil, Joseph; 235 Hills Road, Cambridge CB2 2RW (GB).

(74) Agent: FLINT, Adam; W.H. Beck, Greener & Co., 7 Stone Buildings, Lincoln's Inn, London WC2A 3SZ (GB).

(81) Designated States (*national*): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NO, NZ, PH, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR, TT, TZ, UA, UG, UZ, VN, YU, ZA, ZW.


(84) Designated States (*regional*): ARIPO patent (GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

Published:

— without international search report and to be republished upon receipt of that report

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

(54) Title: SEMICONDUCTOR DEVICE AND METHOD OF FORMING A SEMICONDUCTOR DEVICE



(57) Abstract: A power semiconductor device (10) has an active region that includes a drift region (20). At least a portion of the drift region (20) is provided in a membrane (16) which has opposed top and bottom surfaces (15, 17). In one embodiment, the top surface (15) of the membrane (16) has electrical terminals connected directly or indirectly thereto to allow a voltage to be applied laterally across the drift region (20). In another embodiment, at least one electrical terminal is connected directly or indirectly to the top surface (15) and at least one electrical terminal is connected directly or indirectly to the bottom surface (17) to allow a voltage to be applied vertically across the drift region (20). In each of these embodiments, the bottom surface (17) of the membrane (16) does not have a semiconductor substrate positioned adjacent thereto.

-1-

SEMICONDUCTOR DEVICE
AND METHOD OF FORMING A SEMICONDUCTOR DEVICE

The present invention relates to a semiconductor
5 device and to a method of forming a semiconductor device.

The present invention is particularly concerned with
high voltage/power semiconductor devices which can be used
as discrete devices, in hybrid circuits and in power
10 integrated circuits and is particularly concerned with
field-effect transistors, such as power MOSFETs, insulated
gate bipolar transistors (IGBTs) and other types of power
devices such as diodes, transistors and thyristors.

15 For devices designed for use in integrated circuits,
it is preferred that the main terminals (variously called
the anode/cathode, drain/source and emitter/collector) and
the control terminals (termed the gate or base) are placed
at the surface of the device in order to be easily
20 accessible. The main current flow is between the main
terminals and is therefore principally lateral. Such
devices are therefore typically referred to as lateral
devices. Such devices are often integrated with low-
voltage devices or circuits built in CMOS-type or other
25 standard planar technologies to form power integrated
circuits. Several high voltage/power devices may be
integrated in the same chip. Isolation is provided between
the high-power and the low-power devices as well as between
adjacent power devices. Two principal isolation
30 technologies have emerged, namely junction-isolation (JI)
technology and silicon-on-insulator (SOI) technology.

-2-

In JI technology, a reverse-biased junction is used to isolate adjacent devices. However, this is in many cases not satisfactory for power integrated circuits since minority carrier conduction through the semiconductor substrate (on which the active part of the device is formed) can take place and interference between adjacent devices is therefore difficult to prevent. In addition, JI bipolar devices (such as the lateral IGBT) also suffer from parasitic mobile carrier plasma stored in the semiconductor substrate in the on-state which has to be removed during turn-off. This decreases dramatically the switching speed of the devices.

In SOI technology, a buried insulating layer is used to isolate vertically the top semiconductor layer from the bottom semiconductor layer and, accordingly, current conduction is principally restricted to the top semiconductor layer and there is practically no current in the bottom semiconductor layer in any mode of operation. Horizontal or lateral isolation in SOI is typically provided via trenches which are filled with oxide or by use of the known LOCOS ("local oxidation of silicon") isolation. SOI technology offers better isolation than JI technology because the buried insulating layer prevents current conduction and plasma formation in the substrate.

High voltage semiconductor devices have incorporated within the body of the device a high voltage junction that is responsible for blocking the voltage. This junction includes a relatively lowly doped semiconductor layer which withstands the largest portion of the voltage across the main terminals when the device is in the off-state and operating in the voltage blocking mode. This layer is

-3-

commonly referred to as the drift region or layer and is partially or fully depleted of minority carriers during this operating mode. Ideally, the potential is equally distributed along the drift region between the two ends of the drift region. However, as shown by the 1-D Poisson equation, for a given doping of the drift region, the distribution of the electric field has a triangular shape or, when fully depleted, a trapezoidal shape. Since the area underneath the electric field can be approximated as the breakdown voltage when the peak of the electric field reaches the critical electric field in the semiconductor, it is obvious that for a 1-D junction, the lower the doping of the drift layer, the higher the breakdown voltage. However, for majority carrier devices such as MOSFET types, known as LDMOSFETs, the on-state resistance of the drift layer is inversely proportional to the doping of the drift layer. Since a low on-resistance is desired for a high voltage switch, it follows that a low doping concentration affects the on-state performance of the device. In addition for lateral devices, the critical electric field at the surface is smaller than in the bulk, adding further difficulties in designing high voltage lateral devices.

The introduction of the RESURF (Reduced Surface Field Effect) technique for JI devices allows an increase in the breakdown voltage of lateral devices through the use of an additional vertical junction formed between the drift region and the semiconductor substrate. Figure 1a shows schematically a conventional JI diode using the RESURF effect. This diode is provided as part of a conventional lateral power device such as a lateral transistor, LDMOSFET or LIGBT. Figure 1a also shows the distribution of the potential lines and the edge of the depletion region during

- 4 -

the voltage blocking mode. It can be noted that the drift layer 1 is fully depleted but the semiconductor substrate 2 is not fully depleted. The potential lines bend as they drop in the substrate, from the vertical direction towards the horizontal direction, such that below the high voltage terminal 3, the potential lines are practically parallel to the bottom surface 4 of the substrate 2. This is because the thickness of the semiconductor substrate 2 is relatively large (typically 300 μ m) compared to the vertical extension of the depletion region from the top surface 5 into the substrate 2 (typically 60 μ m for a 600V device). Hence, the semiconductor substrate 2 is not fully depleted when the breakdown of the device occurs. It is known that a lateral JI diode can achieve breakdown voltages equivalent to those of vertical diodes, in spite of the reduced surface critical electric field. Nevertheless, as shown in Figure 1a, even an optimised electric field distribution using the RESURF concept is far from being ideal (i.e. rectangular in shape). In addition as already mentioned, the JI devices suffer from high leakage currents and very poor isolation, which makes integration within a power integrated circuit very difficult.

Figure 1b shows a conventional SOI diode which is typically found as part of a SOI lateral high voltage power device. The structure can be made using the known wafer bonding, Unibond or SIMOX SOI technologies. Other technologies such as Silicon-on-Diamond (SOD) are also known. Figure 1b also shows the equi-potential line distribution during the voltage blocking mode. It can be seen that the potential lines crowd towards the edges of the drift layer 1, resulting in a poor RESURF effect.

-5-

Increasing the thickness of the buried oxide 6 helps to redistribute the potential lines more evenly at the top surface 5. However, in general, the breakdown voltage is still below that of a JI device or JI diode as shown in Figure 1a. Again, the potential lines in the drift layer 1 and the buried silicon oxide insulating layer 6 below the high voltage terminal are practically aligned to the horizontal surface. This is due to the fact that the semiconductor substrate 2 is not entirely depleted. The result is that all the potential lines have to crowd into the drift layer 1 and insulating layer 6 in the case of SOI and moreover have to align parallel to the insulating layer 6/semiconductor substrate 2 interface. This creates an uneven distribution of the potential lines at the top surface 5 which results in high electric field peaks and therefore lower breakdown voltages. In addition, for SOI devices, the conservation of the perpendicular component of the electric flux density $D = \epsilon E$ at the top of the semiconductor layer 1/buried oxide 6 interface limits the maximum voltage that the buried oxide 6 can sustain before the critical electric field in the semiconductor layer 1 at the interface is reached. This vertical breakdown yields a very strong limitation on the maximum voltage rating achievable for a given buried oxide thickness.

25

Thus, in summary, in both JI and SOI devices, the potential lines have to bend from a vertical orientation to a horizontal or lateral orientation and the potential distribution in the drift layer is far from ideal.

30

Moreover, when a power integrated circuit made in thin SOI technology comprises at least a half-bridge configuration, which involves two power devices operating

-6-

in different modes, the device operating in the high side mode may suffer from pinch-off of the drift region during the on-state. This is due to the high electric field in the drift region caused by the high negative potential
5 created in the semiconductor substrate with respect to the potential of one of the main terminals of the high-side device.

It is therefore apparent that the semiconductor
10 substrate in the SOI technology is not passive in all operation modes and its presence results in a poor distribution of the potential lines during the voltage blocking mode, which may cause premature breakdown commonly at the surface of the semiconductor or at the buried
15 oxide/top semiconductor interface due to vertical breakdown. The JI approach suffers from very poor isolation within the power integrated circuit and the breakdown voltage, although generally higher than in the SOI devices, is still lower than would be preferred.

20

For discrete devices or hybrid circuits used in high voltage or power electronics, it is preferred that the main terminals have a vertical orientation and are placed at opposite sides of the wafer (e.g. with the low voltage
25 terminal at the top and the high voltage terminal at the bottom). These devices are referred to as vertical high voltage/power devices. Compared to lateral devices, the current flow between the main terminals is principally vertical and this results in a larger current capability
30 and a higher breakdown voltage. Such devices are however difficult to use in integrated circuits. Example of known high voltage/power devices are DMOS & Trench MOSFETs, DMOS & Trench IGBTs and Cool MOS.

-7-

For an optimised trade-off between on-state/
switching/breakdown performance, the vertical devices
require a narrow drift region that is preferably fully
5 depleted at full voltage blocking. Such a layer may have a
thickness from 6 μ m to 180 μ m for devices rated from 50 V to
1.2 kV. Commonly the drift layer lies on a highly doped
semiconductor substrate. The semiconductor substrate
however introduces a series of negative effects on the
10 general performance of the device. First, it introduces a
parasitic resistance, which leads to increased on-state
power losses. Secondly, for bipolar devices with anode
injection such as IGBTs, since the doping of the substrate
is high, to reduce the power losses in the substrate
15 resistance, the injection from the substrate which acts as
the anode (emitter) of the device is in most cases too
strong, leading to high transient switching losses and slow
turn-off due to the a large amount of plasma stored inside
the drift region during on-state. Thirdly, the substrate
20 introduces a thermal resistance which prevents effective
dissipation of heat to an external sink placed at the
bottom of the device. Finally, if vertical devices are to
be used in integrated circuits, the presence of the thick
semiconductor substrate makes isolation between adjacent
25 devices very difficult.

There have been numerous prior proposals for
increasing the breakdown voltage of semiconductor devices,
particularly power semiconductor devices. Examples are
30 disclosed in US-A-5241210, US-A-5373183, US-A-5378920,
US-A-5430316, US-A-5434444, US-A-5463243, US-A-5468982,
US-A-5631491, US-A-6040617, and US-A-6069396. However,
none of these prior art proposals has tackled the problem

-8-

of increasing the breakdown voltage by a detailed consideration of the electric potential lines in the drift region.

- 5 In WO-A-98/32009, there is disclosed a gas-sensing semiconductor device. A gas-sensitive layer is formed over a MOSFET heater which is used to heat the gas-sensitive layer. The substrate on which the device is formed is back-etched to form a thin membrane in the sensing area.
- 10 It should be noted that the MOSFET heater is a low voltage device (and as such does not have a drift region) and, furthermore, the thin membrane is formed below the MOSFET heater solely to facilitate heating of the sensing area to very high temperatures and not to affect the field or
- 15 potential lines in the device.

- US-A-5895972 discloses a method and apparatus for cooling a semiconductor device during the testing and debugging phases during development of a device. In place
- 20 of conventional heat slugs such as copper, a heat slug of material that is transparent to infra red is fixed to the device. A diamond heat slug is disclosed as preferred. It is disclosed that the substrate on which the device is formed can be thinned prior to applying the infra red
- 25 transparent heat slug to the device. The purpose of this thinning of the substrate is to reduce transmission losses that occur during optical testing and debugging of the device using infra red beams. There is no discussion of the type of semiconductor device to which the heat slug is
- 30 applied and there is no disclosure that the device is a power device having a drift region. Moreover, as stated, the purpose of the thinning of the substrate and application of the heat slug is solely to facilitate

-9-

testing of the device using optical testing and debugging. This process is carried out during development of the device. The heat slug is not used during normal operation of the device.

5

There have been a number of proposals in the prior art for semiconductor devices which make use of a so-called membrane. Examples include US-A-5420458, WO-A-94/22167, US-A-3689992 and US-A-6008126. In the case of each of
10 these prior art proposals, the semiconductor device is not a power device and thus does not have a drift region. In each case, the membrane arrangement is used to provide for isolation between semiconductor devices in an integrated circuit or between regions within a semiconductor device
15 and/or to remove or lower coupling parasitic capacitances. In each case, since these are low voltage devices, the breakdown voltage is virtually unaffected by the membrane structure.

20 According to a first aspect of the present invention, there is provided a power semiconductor device having an active region that includes a drift region, at least a portion of the drift region being provided in a membrane having opposed top and bottom surfaces, the top surface of
25 the membrane having electrical terminals connected directly or indirectly thereto to allow a voltage to be applied laterally across the drift region, the bottom surface of the membrane not having a semiconductor substrate positioned adjacent thereto.

30

According to a second aspect of the present invention, there is provided a power semiconductor device having an active region that includes a drift region provided in a

-10-

layer, the layer being provided on a semiconductor substrate, at least a portion of the semiconductor substrate below at least a portion of the drift region being removed such that said at least a portion of the
5 drift region is provided in a membrane defined by that portion of the layer below which the semiconductor substrate has been removed, the top surface of the membrane having electrical terminals connected directly or indirectly thereto to allow a voltage to be applied
10 laterally across the drift region.

According to a third aspect of the present invention, there is provided a power semiconductor device having an active region that includes a drift region, at least a
15 portion of the drift region being provided in a membrane having opposed top and bottom surfaces, at least one electrical terminal connected directly or indirectly to the top surface and at least one electrical terminal connected directly or indirectly to the bottom surface to allow a
20 voltage to be applied vertically across the drift region, the bottom surface of the membrane not having a semiconductor substrate positioned adjacent thereto.

According to a fourth aspect of the present invention,
25 there is provided a power semiconductor device having an active region that includes a drift region provided in a layer, the layer being provided on a semiconductor substrate, at least a portion of the semiconductor substrate below at least a portion of the drift region
30 being removed such that said at least a portion of the drift region is provided in a membrane defined by that portion of the layer below which the semiconductor substrate has been removed, and at least one electrical

-11-

terminal connected directly or indirectly to the top surface and at least one electrical terminal connected directly or indirectly to the bottom surface to allow a voltage to be applied vertically across the drift region.

5

The said at least a portion of the drift region is fully or substantially fully depleted of mobile charge carriers when a voltage is applied across terminals of the device. In the first and second aspects of the present invention, the potential lines in said at least a portion of the drift region are substantially perpendicular to the top and bottom surfaces of the membrane and substantially uniformly spread laterally across said at least a portion of the drift region. This in turn leads to a higher breakdown voltage which may approach the ideal or theoretical limit. In the third and fourth aspects, the potential lines in said at least a portion of the drift region are substantially parallel to the top and bottom surfaces of the membrane and substantially uniformly spaced vertically across said at least a portion of the drift region.

Thus, in the preferred embodiments, the absence of the semiconductor substrate under at least a portion of the depletion region in lateral devices leads to enhanced breakdown ability due to a more favourable electric field and potential distribution within the drift region of the power device. For vertical devices, the absence of the semiconductor substrate allows the formation of a thin drift region and removes parasitic effects such as the parasitic series electrical resistance and substrate thermal resistance.

-12-

Power devices typically operate with a voltage in the range 30V to 1.2 kV and a current in the range 100mA to 50A. Their application may range from domestic appliances, electric cars, motor control, and power supplies to RF and microwave circuits and telecommunication systems.

It will be appreciated that the terms "top" and "bottom", "above" and "below", and "lateral" and "vertical", are all used in this specification by convention and that no particular physical orientation of the device as a whole is implied.

The so-called membrane power device of the present invention may be of many different types, including for example a diode, a transistor, a thyristor, a MOS controllable device such as a MOSFET, an insulated gate bipolar transistor (IGBT), a double gate device, etc.

In the preferred embodiments discussed further below, there is provided a high voltage, power device with high breakdown voltage capacity coupled with excellent isolation and reduced self-heating.

The arrangement may be such that only part of the drift region is provided in the membrane.

In the first and second aspects, where only a part of the drift region is provided in the membrane, preferably the high voltage terminal end of the drift region is contained within the membrane; the remainder of the drift region, including the low voltage terminal end, may remain outside the membrane.

-13-

In the third and fourth aspects, the device edge termination may be provided outside the membrane while the active region which includes part of the drift region is
5 provided within the membrane.

In any aspect, the whole of the drift region may be provided in the membrane.

10 At least one isolation layer may surround the drift region. The at least one isolation layer may be provided in said membrane or in a separate membrane to extend from the top surface of the membrane to the bottom surface of the membrane.

15 At least one isolation layer may surround the drift region and be provided outside the membrane.

The or at least one isolation layer may be provided by
20 electrically insulating material. The or at least one isolation layer may be provided by a highly doped semiconductor layer which in use is biased to provide a junction that is reverse-biased or biased below the forward-bias level.

25 There may be provided at least one additional power device having a drift region at least a portion of which is provided on said membrane or on a separate membrane. The separate membrane is preferably formed over the same
30 original substrate and preferably in the same fabrication step with the or each other membrane provided in the device.

-14-

There may be provided at least one low voltage device. Said at least one low voltage device may be provided in said membrane. Alternatively, said at least one low voltage device may be provided outside said membrane. In
5 that case, said at least one low voltage device may be provided in a further membrane, said further membrane being preferably formed over the same original substrate and preferably within the same fabrication step with the other membranes provided in the device. In either case, this
10 arrangement provides a power integrated circuit. The low voltage device or devices may be for example a bipolar or CMOS circuit. Such low voltage power devices may form driving, protection or processing circuits. In the preferred embodiments discussed below, the membrane power
15 devices are well isolated both vertically and laterally from such low voltage devices. The vertical isolation is achieved by virtue of the absence of the parasitic substrate beneath the active region of the power device. Lateral isolation can be achieved as briefly described
20 above by one or more isolation layers provided preferably in a membrane from the top to the bottom surface of the membrane or outside the membrane.

There may be at least one isolation layer providing
25 electrical isolation between adjacent devices. The said isolation layer may be placed on a further membrane, said further membrane preferably being formed over the same original substrate and preferably within the same fabrication step with the or each other membrane provided
30 in the device.

-15-

In the first and second aspect of the present invention, the device may comprise an electrically insulating and thermally conductive layer adjacent to the bottom surface of the membrane. The electrically
5 insulating and thermally conductive layer is used to help remove a large part of the heat that might otherwise be trapped within the membrane when the power device is operating. The layer may be of any suitable material such as for example polycrystalline diamond, amorphous diamond,
10 boron nitride, aluminium oxide, etc. The material is preferably formed by blank deposition as a layer by sputtering or chemical vapour deposition or any other suitable technique. The layer may entirely fill the space under the membrane or may be provided as a thin layer under
15 the membrane and which follows the side walls and the bottom surface of any remaining substrate. The layer is preferably in thermal contact with a heat sink.

In the third and fourth aspects, the bottom terminal
20 may be electrically and thermally conductive. The bottom terminal may be made of a metal or a combination of metals such as aluminium, copper etc. The bottom terminal may fill the space under the membrane. In a preferred embodiment, the bottom terminal is provided as a thin layer
25 under the membrane that follows down side walls of any remaining substrate and under the main bottom surface of the device. This layer is preferably in thermal contact with an external heat sink. Alternatively, more than one bottom terminal, in the form of thin layers isolated from
30 one another, can be placed at the bottom of one or separate membranes.

-16-

The membrane may comprise a semiconductor layer provided on an electrically insulating layer. The electrically insulating layer may be an oxide layer as formed in for example known SOI technology. Where
5 substrate is etched away to form the membrane, such an oxide layer conveniently acts as an etch stop, which assists in the formation of the membrane. In the third and fourth aspects, this layer is removed to provide access for the terminal layer to be provided at the bottom.

10

In the first and second aspects, the device may comprise a mechanically strong and electrically insulating layer provided under the membrane. The mechanically strong and electrically insulating layer provides structural
15 support to the membrane and also acts to minimise the risk of membrane rupture.

In any aspect, the drift region may have a non-uniform doping profile. This helps to ensure that the potential
20 lines in the drift region are substantially uniformly spread across the drift region. This in turn leads to a higher breakdown voltage which may approach the ideal or theoretical limit. The doping concentration of the drift region at a high voltage terminal side of the device is
25 preferably relatively high and the doping concentration of the drift region at a low voltage terminal side of the device is preferably relatively low. The doping concentration of the drift region may vary linearly from one side of the drift region to the other. This serves to
30 improve further the breakdown capability of the device.

-17-

In the first and second aspects, the drift region may comprise at least two semiconductor layers of alternating conductivity type arranged one above the other and in contact with each other. In use, these two or more
5 semiconductor layers of alternating conductivity type provide a semiconductor junction in a vertical direction such that the drift region can be fully depleted of mobile charge carriers when a voltage is applied across terminals of the device. This again helps to ensure that the
10 potential lines in said at least a portion of the drift region are substantially perpendicular to the top and bottom surfaces of the membrane and substantially uniformly spread laterally across said at least a portion of the drift region. This in turn leads to a higher breakdown
15 voltage which may approach the ideal or theoretical limit.

In any aspect, the drift region may comprise a plurality of laterally adjacent semiconductor regions of alternating conductivity type. These laterally adjacent
20 semiconductor regions of alternating conductivity type form plural transverse junctions in the "z" direction of the device, which again helps to ensure that the potential lines in said at least a portion of the drift region are substantially uniformly spread across said at least a
25 portion of the drift region. This in turn leads to a higher breakdown voltage which may approach the ideal or theoretical limit.

In any aspect, the drift region may comprise a
30 plurality of laterally adjacent semiconductor cells of alternating conductivity type arrayed around the plane of the device. The cells may be arranged in a regular or an irregular pattern. Either arrangement again helps to

-18-

ensure that the potential lines in said at least a portion of the drift region are substantially uniformly spread across said at least a portion of the drift region. This in turn leads to a higher breakdown voltage which may
5 approach the ideal or theoretical limit.

The device may comprise a termination region adjacent to and in contact with the drift region, said termination region being provided to reduce the effect of premature
10 breakdown at the edge of the drift region. At least a portion of the said termination region may be placed inside the membrane. At least a portion of the said termination region may be placed outside the membrane and above any semiconductor substrate. The drift region may be more
15 highly doped than at least a portion of the termination region. The drift region may be more highly doped than the semiconductor substrate.

According to a fifth aspect of the present invention,
20 there is provided a method of forming a power semiconductor device having an active region that includes a drift region, the method comprising the steps of: forming, in a layer provided on a semiconductor substrate, a power semiconductor device having an active region that includes
25 a drift region; and, removing at least a portion of the semiconductor substrate below at least a portion of the drift region such that said at least a portion of the drift region is provided in a membrane defined by that portion of the layer below which the semiconductor substrate has been
30 removed.

-19-

It is preferred that the substrate be removed as the last or one of the last steps in the device fabrication process. In that way, the substrate provides support for the device for as long as possible during the fabrication
5 process.

Said at least a portion of the semiconductor substrate may be removed by wet etching.

10 Said at least a portion of the semiconductor substrate may be removed by dry etching.

Said at least a portion of the semiconductor substrate may be removed using a buried insulating layer as an etch
15 stop. The burial layer may be part of a Silicon-on-Insulator (SOI) structure.

At least one semiconductor layer may be introduced by implantation, diffusion or deposition from the back-side of
20 the device following the formation of the membrane.

A bottom terminal layer may be applied to the bottom of the membrane, said bottom terminal layer being in contact with at least one semiconductor layer within the
25 membrane.

The method may comprise the step of applying an electrically insulating and thermally conductive layer adjacent the bottom surface of the membrane. The
30 electrically insulating and thermally conductive layer may be applied by a (preferably blank) deposition process.

-20-

Alternatively the method may comprise the step of applying an electrically and thermally conductive layer which acts as an electrode (terminal) adjacent the bottom surface of the membrane. Said layer may be applied by a
5 blank deposition.

In formation of the devices and in the methods described above, one or more of bipolar, CMOS, Bi-CMOS, DMOS, SOI, trench technology or known integrated circuit
10 fabrication steps may be employed.

In the devices and methods described above, the drift region may comprise at least one of silicon, silicon carbide, diamond, gallium nitride and gallium arsenide.
15

Where provided, at least one of the insulating layers may comprise one of silicon dioxide, nitride, diamond, aluminium oxide, aluminium nitride and boron nitride.

20 Embodiments of the present invention will now be described by way of example with reference to the accompanying drawings, in which:

Fig. 1a is a schematic cross-sectional view of a prior
25 art JI power diode;

Fig. 1b is a schematic cross-sectional view of a prior art SOI power diode;

30 Fig. 2a is a schematic perspective view of a first example of a device according to the present invention;

-21-

Fig. 2b is a schematic perspective view of a second example of a device according to the present invention;

Fig. 3 is a schematic cross-sectional view of another example of a device according to the present invention in which the potential lines are illustrated; and,

Figures 4 to 43 are schematic cross-sectional or perspective views of further examples of devices according to the present invention.

Referring now to Figures 2a and 2b, first and second examples of a membrane power semiconductor device 10 according to the present invention each have a semiconductor substrate 11 having a bottom surface 12 that forms the main bottom surface of the device 10. A first thin layer 13, which in these examples comprises a semiconductor layer 14, is formed on the substrate 11 and has a top surface 15 that forms the main top surface 5 of the device 10. The original full extent of the substrate 11 is indicated in Figures 2a and 2b by dashed lines.

During manufacture, a portion 11' of the substrate 11 below the thin layer 13 is entirely removed up to the thin layer 13 in order to leave a region of the thin layer 13 below which there is no substrate 11, this region being referred to herein as a membrane 16 (shown within the dot and dashed lines). The remaining portions of the substrate 11 form support legs. The membrane 16 has a bottom surface 17. The active structure 18 of the power device 10 (indicated by dotted lines) is in these examples located entirely within the membrane 16. In the example of Figure 2a, the active structure 18 is electrically isolated from other devices or circuits by an isolation layer 19 formed within

-22-

the membrane 16 between the top surface 15 and the membrane bottom surface 17 such that the isolation layer 19 surrounds the active structure 18 of the power device 10. In the example of Figure 2b, the isolation layer 19 is provided outside the membrane 16 within the thin layer 13 such that it surrounds the active structure 18 of the power device 10. In the examples of both Figure 2a and 2b, the power device 10 contains a drift layer 20 that is placed in the semiconductor layer 14 inside the first thin layer 13 and entirely within the membrane 16. The drift layer 20 supports high voltages applied across the main terminals (not shown) of the power device 10 whilst the power device 10 is off and blocks the voltage across the main terminals. During such operating mode, the drift layer 20 becomes partially or ideally completely depleted of mobile carriers. According to an embodiment of this invention, if the main terminals are placed on the top surface 15 of the device and within the membrane 16, the equi-potential lines in a cross-section of the device along the drift layer 20 are practically perpendicular to both the main top surface 15 and the membrane bottom surface 17. According to another embodiment of this invention, if a first main terminal is placed on the surface 15 and within the membrane 16 and a second main terminal is placed adjacent to the bottom membrane and within the membrane 16, the potential lines are practically parallel to both the top and bottom surfaces 15,17.

It is preferred that the substrate portion 11' be removed as the last or one of the last fabrication steps, and particularly after formation of all or substantially all of the structures in and above the thin layer 13 has been completed, so that the entire substrate 11 can support

-23-

the whole of the thin layer 13 during these fabrication steps.

It is worth pointing out here the differences in the two-dimensional potential distribution of prior art high voltage devices, such as conventional junction-isolation (JI) high voltage devices or Silicon-on-Insulator (SOI), and the membrane power devices according to this invention. As can be seen in Figures 1a and 1b, for the conventional devices, the potential lines are virtually perpendicular to the top surface 5, but as they drop into the body of the device, they align to be parallel to the bottom substrate surface 4. Such distribution of the potential lines may lead to premature breakdown. Figures 3a and 3b show the two-dimensional distribution of the potential lines in an example of a simple power device structure according to the present invention formed by one single high voltage junction. In the example of Figure 3a, the main terminals 23 are placed on the top surface 15 and the drift region 20 contains for simplicity only one semiconductor layer which is more lowly doped than the p+ anode region 21 and the n+ cathode region 22. This drift region 20 becomes completely depleted during the voltage blocking mode and before the breakdown occurs. Referring to Figure 3a in comparison with Figure 1a and Figure 1b, it can be seen that the potential lines are perpendicular or near perpendicular to both the top surface 15 and the bottom surface 17 of the membrane 16, and substantially uniformly distributed from the anode region 21 to the cathode region 22 inside the drift region 20 such that the value of the breakdown voltage approaches its ideal limit. In the example of Figure 3b, the main terminals 23 are on the top surface 15 and bottom surface 17 respectively such that the potential

-24-

lines are parallel or near parallel to both the top surface 15 and the bottom surface 17, and substantially uniformly distributed from the anode region 21 to the cathode region 22 inside the drift region 20 such that the breakdown voltage is ideal for a given thickness of the drift layer 20.

The preferred embodiments of high voltage power devices according to the present invention also differ from the prior art devices in the way the isolation is achieved. The isolation in the preferred membrane power devices is realised vertically in a perfect manner through the absence of substrate below the active structure 18 of the membrane power device 10 and is achieved laterally through the use of an isolation layer 19 which surrounds the active structure 18 of the power device 10.

Where provided, the isolation layer 19 may be in the form of a highly doped semiconductor layer connected to a matched voltage so that all the junctions associated with said isolation layer are reverse biased or zero biased. In this case, the isolation layer acts as an effective conduction barrier. Figures 4a and 4b each show an example of a membrane power device 10 having a p+ isolation layer 19 which extends from the top surface 15 to the bottom membrane surface 17 and which surrounds the active structure 18. The p+ isolation layer 19 is connected to ground, which in these examples is assumed to be the lowest potential available in the power integrated circuit. In the example of Figure 4a, the isolation layer 19 is provided within the membrane 16. In the example of Figure 4b, the isolation layer 19 is provided outside the membrane 16.

-25-

The isolation layer may alternatively be made of an insulating layer such as silicon oxide and may be in the form of a trench or LOCOS layer. As a yet further
5 alternative, the isolation can be made by trenches filled with a sandwich of oxide and polysilicon layers. Other insulation materials can also be used. Another alternative is to use air gaps (so-called "MESA" or "trench" \ isolation).

10

Several isolation layers 19 may be used within the same membrane 16 to separate plural power devices 10 placed within the same membrane 16 or to separate bipolar or CMOS low voltage devices from the power devices 10. Referring
15 to Figure 5a, there is shown an example of four such power devices 10 placed within the same membrane 16 and isolated from each other through isolation layers placed within the membrane 16. Referring to Figure 5b, there is shown a top view of an example of four power devices 10 placed on
20 separate respective membranes 16 and isolated from each other through isolation layers 19 placed outside the membranes 16. Referring to Figure 6a, there is shown a schematic 2D cross-section of a power integrated circuit 40 which contains one membrane power device 10 and CMOS and
25 bipolar devices 41 placed outside the membrane 16. Alternatively, the CMOS and bipolar devices 41 can also be placed on the membrane 16 together with the power devices 10 as shown in Figure 6b or on different membranes 16 formed over the same original substrate 11 as shown in
30 Figure 6c. The example of Figure 6d differs from the example of Figure 6c in that the isolation layer 19 is placed outside the membranes 16. It is evident that the use of the membranes 16 and isolation layers 19 can provide

-26-

a very effective electrical isolation between the power devices 10 and the low power circuits 41 as well as between adjacent power devices 10.

5 Referring now to Figure 7, considering that all of the terminals are placed on the top surface 15 in this example, a layer 45 that is electrically insulating but which has a relatively high thermal conductivity may be placed adjacent the bottom surface 17 of the membrane 16 to help remove a
10 large fraction of the heat which otherwise may be trapped inside the membrane 16 while the power device is operational. In the preferred embodiment, this layer 45 is formed after the single back-side etching of the semiconductor substrate 11 is carried out and may be in the
15 form of a blank deposition of a dielectric material with high thermal conductivity. Such material may be for example based on diamond. Other materials, such as boron nitride, aluminium nitride, and aluminium oxide, can be used. As shown in Figure 8, the insulating layer 45 may
20 fill the entire gap in the substrate 11 left by the membrane formation. In either case, a heat sink 46 may be in thermal contact with the insulating layer 45 to extract heat.

25 As shown in Figures 9a and b, the first thin layer 13 may comprise a thin insulating layer 50, the bottom of which effectively forms the membrane bottom surface 17, and at least one semiconductor layer 51 placed on top of the thin insulating layer 50, as known in for example state-of-
30 the-art Silicon-on-Insulator (SOI) technology. In this case, an SOI technology such as bonding wafer, SIMOX or Unibond may be used in the fabrication of the power integrated circuits. Alternatively, silicon or diamond can

-27-

be used. As one of the last steps of the high voltage SOI process, and as in the examples described above, the semiconductor substrate 11 below the buried insulating layer 50 may be partially removed through conventional
5 patterning by single back-side etching. In this example, the buried insulating layer 50 acts as an effective etch stop to form the membrane 16. Importantly, when the main terminals are placed on the top surface 15 and within the membrane 16, the buried insulating layer 50 also helps
10 achieve a uniform distribution of the potential lines inside the drift layer 20 such that the breakdown voltage of the membrane power device 10 will be close to its ideal value. In the example of Figure 9a, the isolation layer 19 is placed within the membrane 16. In the example of Figure
15 9b, the isolation layer 19 is provided outside the membrane 16.

Again, an insulating layer 45 with relatively high thermal conductivity may be formed below the membrane 16 as
20 shown in Figures 10 and 11 to help remove the heat laterally to the substrate 11 and/or directly to an external heat sink 46. In the examples of Figures 10a and 11a, an isolation layer 19 is provided within the membrane 16 whereas in the examples of Figures 10b and 11b, an
25 isolation layer is provided outside the membrane 16.

In the example shown in Figure 12, a further electrically insulating layer 55 with enhanced mechanical properties is placed between the buried insulating layer 50
30 and the electrically insulating but thermally conductive layer 45 in the region of the membrane 16 in order to strengthen the structure of the membrane 16 and help minimise the risk of mechanical rupture of the membrane 16.

-28-

This additional insulating layer may also help to compensate the overall mechanical stress in the membrane 16 and may also enhance the adhesion of the electrically insulating but thermally conductive layer 45 to the buried insulating layer 50. It will be appreciated that this mechanically strong layer 55 can also be placed under the membrane 16 in any of the other examples described in this specification that do not have the buried insulating layer 50, such arrangement enhancing the electrical passivation and/or mechanical performance of the structure including particularly the resistance to rupture. Several such mechanically strong insulating layers can be deposited on the back side of the membrane 16 to increase the thermal dissipation, passivate electrically and/or consolidate mechanically the membrane 16 and/or to act as buffer layers to achieve good adhesion between one layer and another. The insulating layers 21 and buffer layer may be nitrides, oxides, amorphous materials or polycrystalline materials.

In the examples shown in Figures 13a to 13c, when the main device terminals are placed on the top surface 15 and within the membrane 16, the first thin layer 13 in each case comprises two semiconductor layers 60,61 of opposite conductivity type such that the drift region in the power device 10 is now comprised of two semiconductor regions 60',61' of opposite conductivity type placed above and in direct contact with each other to form a semiconductor junction. The presence of these two semiconductor regions 60',61' of different conductivity type and in direct contact can significantly increase the breakdown voltage of the device. This is due to the horizontal junction formed in the vertical direction between the semiconductor layers 60,61 which facilitates the depletion of the entire drift

-29-

region at much lower voltage than the breakdown voltage. This means that the drift region acts physically as an intrinsic layer during the voltage blocking mode and the potential lines in a vertical cross-section of the device are perpendicular to the top surface 15 and the membrane bottom surface 17 and more evenly distributed along the drift region in the lateral direction. For these structures, the electric field is therefore practically uniform along the drift region in the lateral or x direction. If the electric field reaches its critical value, avalanche breakdown occurs. As the electric field at this point is substantially uniform, the breakdown voltage, which is graphically represented by the area under the electric field curve in the x direction between the main terminals of the device, is a maximum. It will be understood that the doping concentration and the thickness of the two semiconductor layers 60,61 each play an important role in obtaining the maximum breakdown voltage possible and are preferably selected such that the entire drift region is depleted at relatively low voltage compared to the rated breakdown voltage. The choice of doping concentration and thickness of the two semiconductor layers 60,61 is also influenced by the type of power device employed and by the associated fabrication process.

25

The example shown in Figure 13b is of the SOI type having a silicon oxide insulating layer 50. The example of Figure 13c is again of the SOI type having a silicon oxide insulating layer 50 and an electrically insulating but thermally conductive layer 45 deposited on the back side of the insulating layer 50. It will be appreciated that an electrically insulating but thermally conductive layer can

30

-30-

also be deposited on the bottom surface 17 of the membrane 16 of the JI example shown in Figure 13a.

In the examples shown in 14a to 14c, which correspond generally to the examples shown in Figures 13a to 13c, the drift region in each case is formed by several semiconductor layers of alternating conductivity type built on top of each other in the y direction such that the entire drift region becomes completely depleted at relatively low voltage compared to the rated breakdown voltage. Again, it will be appreciated that an electrically insulating but thermally conductive layer 45 can be deposited on the bottom surface 17 of the membrane 16 of any of these examples.

15

In the example shown in Figure 15, when again the main terminals are placed on the top surface 15 within the membrane 16, the drift region of the membrane power device comprises plural adjacent layers 70,71,72 of alternating conductivity type arrayed in the third dimension z. These adjacent semiconductor regions in the z direction form transverse semiconductor junctions in the z direction such that the entire drift region becomes completely depleted at relatively low voltage compared to the rated breakdown voltage. The presence of the vertical junction planes in the z direction on the membrane 16 results in an even distribution of the potential lines along the drift region in the x direction, which increases the breakdown voltage to be close to the ideal value. As in the examples described above, the potential lines in a vertical (x,y) cross-section of the device are perpendicular to the top surface 15 and the membrane bottom surface 17 and are thus aligned to the y axis. The doping and the thickness of the

-31-

adjacent semiconductor layers 70,71,72 of different conductivity type are selected such that the drift region depletes entirely in the voltage blocking mode at relatively low voltage compared to the rated breakdown voltage, thus increasing the breakdown voltage close to its ideal value. It will be understood that whilst three semiconductor layers 70,71,72 are shown arrayed in the z direction, just two or more than three such layers may be employed. It will further be understood that an electrically insulating but thermally conductive layer may be deposited on the bottom surface 17 of the membrane 16 in order to extract heat from the device 10.

In the example shown in Figure 16, the drift region is formed by several cells 80 of different conductivity type placed alternately to each other to form at the top surface 15 and in the x,z plane regular patterns such that again the entire drift region becomes completely depleted during the voltage blocking mode so that the potential is distributed uniformly across the drift region. The cells of different conductivity type may be formed regularly as shown or irregularly (not shown) in the x,y plane.

In the examples shown in Figures 17a to 17c (which show respectively a JI device, a SOI device, and a SOI device having an electrically insulating but thermally conductive layer 45 applied to the back of the membrane 16), the substrate 11 is removed such that only a part of the drift region 20 lies within the membrane 16. Thus, part of the drift region 20 remains outside the membrane 16 (and is therefore positioned above the remaining part of the substrate 11). The main terminals are placed on the top surface 15 but, preferably, the high voltage terminal

-32-

end of the drift region 20 is located within the membrane 16 whilst the low voltage terminal end of the drift region 20 may remain outside the membrane 16. Again, it will be appreciated that an electrically insulating but thermally
5 conductive layer 45 can be deposited on the bottom surface 17 of the membrane 16 of any of these examples.

In all of the examples described above and shown in Figures 2 to 17, the walls of the substrate 11 are angled
10 to the x,z plane of the lateral device. This is because the most common technique for back side etching is wet anisotropic etching, which is typically performed using a KOH solution. The silicon substrate 11 is a mono-crystal and the etching rates of anisotropic etchants is dependent
15 on the crystal orientation. The etch-stop planes are usually the (111) planes. Those devices of the SOI type that have the buried oxide layer have the advantage that the back side etch stops automatically at the buried oxide since the etch of the oxide is for many etchants (including
20 KOH) much slower than that of silicon. Alternatively, for bulk silicon (i.e. non-SOI) devices, the back side etch can be controlled in time or electrochemically.

Instead of wet anisotropic etching, dry back side
25 etching may be used for producing any of the membrane power devices according to the present invention. Dry back side etching has the advantage that the walls of the substrate 11 are vertical, as shown by way of example in Figures 18 and 18b. This means that the volume occupied by the gap in
30 the substrate 11 below the membrane 16 is no longer dependent on the thickness of the substrate 11 and thus a plurality of membranes 16 with reduced lateral spacing between them can be achieved in the same chip or integrated

-33-

circuit more easily. In the example of Figure 18a, the isolation layer 19 is provided within the membrane 16 whereas in the example of Figure 18b, the isolation layer 19 is provided outside the membrane 16.

5

In the example shown in Figure 19, the membrane 16 is formed by front side etching (i.e. surface micro machining) of the substrate 11. In the example shown, the substrate 11 is only partly removed below the active region 18 of the device 10 so as to leave a gap in the substrate 11 below the active structure 18 which helps to increase the breakdown capability of the device. Figure 20 is a cross-sectional view of the example of Figure 19. Figure 21 shows a SOI variant of the example of Figures 19 and 20.

10 As in all of the examples described above, the presence of the gap in the substrate 11 below the active region 18 (i.e. the formation of the membrane 16) means that the potential lines in the drift region 20 are perpendicular to both the top surface 15 of the device and the bottom

15 surface 17 of the membrane and are substantially uniformly distributed inside the drift region 20 such that the breakdown voltage approaches its ideal limit.

In the examples shown in Figures 22a and 22b, which are respectively JI and SOI variants, the gap in the substrate 11 is formed only partially under the drift region 20 such that only a part of the drift region 20 is formed in the membrane 16. Again, the main terminals are placed on the top surface 15 but preferably the high

20 voltage terminal end of the drift region 20 is placed within the membrane 16 whilst the low voltage terminal end may remain outside the membrane 16.

25

30

Figure 23a shows in detail an example of a membrane high voltage lateral DMOSFET (LDMOSFET) 10 according to the present invention in which the drift region 20 is of n conductivity type, the source region 90 and the drain region 91 are of n conductivity type and very well doped with donor impurities to form a good ohmic contact, and the p well 92 is of p conductivity type. A conventional insulated gate formed by a thin insulated layer 93 and a polysilicon and/or metal layer 94 is placed above the p well 92 and isolated from the source metal layer S by an insulation layer 95. A thicker insulating layer 96, referred to as the field oxide, may be present at the top of the drift layer 20 between the insulated gate and the drain region. The polysilicon/metal layer 94 may extend by a short distance above the field oxide 96. In the on-state, current flows between the drain terminal D which contacts the n+ drain region 91 and the source terminal which contacts the n+ source region 90. This current is controlled by the potential applied to the gate terminal G which contacts the insulated gate. When a higher potential is applied to the gate terminal with respect to the source terminal, a channel of electrons is formed at the surface of the p well 92 under the insulated gate which allows flow of electrons from the source region, through the channel, via the drift region 20 to the drain. The device can be turned on and off by applying an appropriate potential to the gate terminal. The high voltage LDMOSFET is placed on a membrane 16 defined by the top surface 15 and the membrane bottom surface 17. The membrane bottom surface 17 is situated in the y direction of the cross section between the top surface 15 and the semiconductor substrate surface 12. The membrane 16 is therefore thin in comparison with

-35-

the semiconductor substrate 11 such that when the device operates in the voltage blocking mode, the drift region 20 becomes completely depleted of mobile carriers and the potential lines are virtually perpendicular to the top surface 15 and the bottom membrane surface 17 as shown in Figure 24. This is in contrast with prior art JI LDMOSFETs in which the drift region is conventionally placed above a thick semiconductor substrate which in the off-state is not completely depleted and therefore the potential lines bend from the initial vertical direction in the drift region to align with the horizontal direction (x axis) within the substrate. The advantage of the high voltage membrane LDMOSFET resides in higher breakdown voltage capacity, a more uniform distribution of the potential lines at the surface and a better isolation through the use of a vertical isolation layer 19 in the membrane 16. In this example, the isolation layer 19 is made of a highly doped p+ layer and is connected to the source terminal. It should be understood that the device shown in Figure 23a may typically contain several stripes/fingers/cells such that the device meets the current level and power specifications. For a 600 V device, the drift region doping concentration may typically be $10^{16}/\text{cm}^3$, the thickness of the drift region 20 between 0.2 to 20 μm , and the length of the drift region 30-50 μm . The doping of the drift region 20 need not be constant and can vary from the source end to the drain end. For example, at the source end the doping may be $8 \times 10^{15}/\text{cm}^3$ while increasing linearly to $3 \times 10^{16}/\text{cm}^3$ at the drain end.

30

Figure 23b shows an SOI variant of the example of Figure 23a in which an insulating layer 50 is placed at the

-36-

bottom of the drift region 20 as part of the membrane 16. This insulating layer 50 need not be thick as in the case of prior art SOI high voltage devices but may instead be very thin since the potential in the voltage blocking mode
5 (when the device is off) is not supported across it in the y direction (as in the case of conventional SOI high voltage devices) but instead along it, in the x direction. The isolation in this case is made by trench oxides 19 but other types of isolations, such as p+ layer, may be used.
10 Figure 23c shows a variation of the example of Figure 23b in which an electrically insulating layer 45 with a good thermal conductivity is placed below the membrane to facilitate the removal of heat to a heat sink 46 and thus avoid excessive self-heating. In this example, the
15 isolation layer 19 is provided outside the membrane 16.

Again, it will be appreciated that an electrically insulating but thermally conductive layer 45 can be deposited on the bottom surface 17 of the membrane 16 of
20 any of these examples.

Figures 25a to 25c show in detail examples of Lateral Insulated Gate Bipolar Transistor (LIGBT) membrane power devices in which bipolar current conduction within the
25 drift region 20 suspended on the membrane 16 is employed and which correspond generally to the LDMOSFETs shown in Figures 23a to 23c. The main difference between the LIGBT membrane power devices and the LDMOSFET power devices shown in Figures 23a to 23c is the use of a highly doped p-type
30 hole injector layer 100 at the anode. Bipolar conduction in LIGBT type devices is characterised by conductivity modulation in the drift layer in order to reduce the on-state resistance. Again, it will be appreciated that an

-37-

electrically insulating but thermally conductive layer 45 can be deposited on the bottom surface 17 of the membrane 16 of any of these examples.

5 Figure 26a is a schematic perspective view of an example of a membrane device in the form of a power diode. For a 600 V power diode, the doping concentration of the n drift region 20 is in the range 3×10^{15} to $10^{16}/\text{cm}^3$ with a length of 30 to $50\mu\text{m}$. The thickness of the drift layer 20
10 may be between $0.2\mu\text{m}$ to $20\mu\text{m}$. The doping of the drift region 20 need not be constant and can vary from the source end to the drain end. For example, at the source end the doping may be $8 \times 10^{15}/\text{cm}^3$ while increasing linearly to $3 \times 10^{16}/\text{cm}^3$ at the drain end. For simplicity, only one cell
15 of the diode is shown. Figure 26b shows schematically an SOI version of the power diode shown in Figure 26a in which an insulating layer 50 is formed underneath the drift region 20 which facilitates a more even distribution of the potential lines within the drift region 20 and therefore
20 increases the breakdown ability of the diode. In addition, the insulating layer 50 acts as a very good etch stop and hence it makes formation of the membrane 16 easier. To help remove the heat while the power device is operational, a highly thermally conductive but electrically insulating
25 layer 45 (not shown) may again be placed onto the back of the membrane 16 of the devices shown in Figures 26a and 26b. This layer 45 may be formed by sputtering or other ways of deposition as one of the last processing steps in the fabrication of the power integrated circuit as
30 described above.

-38-

Figure 27a shows schematically an example of a membrane power diode which comprises a drift region 20 formed by two layers 100,101 of different conductivity type n,p arranged vertically one on top of the other. These layers 100,101 may be formed by epitaxial growth or preferably by implant of one layer 101 into the other 102. For a 600 V power diode, the doping concentration of the two semiconductor layers 101,102 forming the drift region 20 may be between 10^{16} and $5 \times 10^{16}/\text{cm}^3$ with a length of 30 to 40 μm . The thickness of the two semiconductor layers 101,102 is between 0.1 μm and 20 μm . If the top semiconductor layer 101 is formed by implant, then the doping concentration of the top layer 101 will be higher than that of the bottom semiconductor layer 102 and hence, in order to maintain spatial charge equilibrium while the drift region 20 is depleted, the thickness of the top layer 101 is preferably less than that of the bottom layer 102. Figure 27b shows schematically an SOI version of the power diode shown in Figure 27a, whereby an insulating layer 50 is formed underneath the drift region 101,102. An additional highly thermally conductive but electrically insulating layer 45 (not shown) may again be placed under the membrane to facilitate the removal of heat, as described previously.

25

Figure 28a shows schematically an example of a 3D membrane power diode. The drift region of the 3D power diode is comprised of several pairs of n,p regions 110,111 disposed in the x,z plane such that they form transverse junctions in the z direction. The widths of these n,p layers 110,111 may typically be between 0.2 μm and 5 μm , which represents a small fraction of their typical length.

-39-

This ensures that the drift region 20 depletes faster in the z direction than in the x direction and therefore behaves similarly to an intrinsic layer in the voltage blocking mode. For a 600V device, the length of the drift regions 20 (in the x direction) may be approximately 30 μm . The doping of the n,p regions 110,111 may be between $10^{15}/\text{cm}^3$ and $6 \times 10^{16}/\text{cm}^3$. Preferably, the n,p regions 110,111 are formed by implanting one layer (e.g. an n layer) 110 into the other layer (e.g. a p layer) 14. Therefore, the doping concentration of the implanted layer 110 is higher than that of the background layer 111 and hence to maintain the charge equilibrium, the width of the implanted layer 110 is preferably smaller than that of the background layer 111. Figure 28b shows schematically a SOI variant of the example of Figure 28a. Again, in each case, an electrically insulating but thermally conductive layer 45 (not shown) may be deposited to extract heat.

Figure 29a shows schematically an example of a single gate membrane 3D LDMOSFET. The device employs the concept described above for the 3D membrane power diode to support a very high voltage between the source and drain terminals while in the voltage blocking mode, whereas in the conduction mode the device is similar to a conventional LDMOSFET and the device of Figure 23a. Figure 29b shows schematically a SOI variant of the example of Figure 28a. Again, in each case, an electrically insulating but thermally conductive layer 45 (not shown) may be deposited to extract heat.

30

Figure 30 shows schematically an example of a double gate membrane 3D LDMOSFET. The device again employs the concept described above for the 3D membrane power diode to

-40-

support a very high voltage between the source and drain terminals. In the conduction mode, the device is controlled via both the n-channel and p-channel gates such that unipolar parallel conduction through the n and p
5 stripes can occur. Bipolar conduction can also take place by injection of electrons into the p drift layer and of holes into the n drift layer.

Referring now to Figure 31, another example of a
10 membrane power semiconductor device 10 according to the present invention has a semiconductor substrate 11 and a thin layer 13 which comprises at least one semiconductor layer 14 and has a top surface 15. The substrate 11 has a bottom surface 12 that forms the main bottom surface of the
15 device. During manufacture, a portion of the substrate 11 below the thin layer 13 is removed up to the thin layer 13 to define a membrane 16 with a top surface 15 and a bottom surface 17. At least one main terminal layer 103 is attached to the bottom surface 17 and in contact with the
20 semiconductor layer 14. In a preferred embodiment, said terminal layer 103 may be in the form of a metal layer deposited from the back side of the device 10 after the membrane 16 is formed by single side back-etching. The metal layer 103 may extend from the membrane bottom surface
25 17 to the main bottom surface 12 of the device 10 and is preferably in contact with an external heat sink. The device comprises at least one further main terminal 104 applied to the top surface 15, in contact with the
30 semiconductor layer 14 and preferably within the membrane 16, such that in the on-state current conduction between the main top terminal 104 and the main bottom terminal 103 is substantially vertical and perpendicular to the top surface 15 and the membrane bottom surface 17. The device

-41-

may have a control terminal 105 placed on the surface 15 to control the current between the main terminals 103,104.

The power device 10 contains a drift layer 20 placed inside the first thin layer 13, within the semiconductor layer 14.

- 5 At least a portion of the drift layer 20 is placed within the membrane 16.

The drift layer 20 supports the high voltages applied across the main terminals 103,104 whilst the power device
10 10 is off and blocks the voltage across the main terminals 103 and 104. During such operating mode, the drift layer 20 becomes partially or completely depleted of mobile carriers and the equipotential lines in a cross-section of the device 10 are parallel with the top surface 15 and the
15 membrane bottom surface 17 and substantially uniformly distributed between the top end of the drift layer 20 and the bottom end of the drift layer 20.

The removal of the substrate 11 under part of the thin
20 layer 13 results in a better trade-off between the on-state resistance and the breakdown performance. The uniform distribution of the potential lines inside the drift region in the membrane 16 results in ideal breakdown voltage for a given thickness of the drift region 20. Because the
25 substrate 11 is removed under part of the thin layer 13, there is no substrate parasitic electrical and thermal resistance and isolation (not shown) from other devices and circuits present in the chip is easier to make. The terminal layer 103 is preferably highly thermally
30 conductive to help dissipation of heat from the membrane region 11 to an external heat sink (not shown).

-42-

Figure 32 shows schematically an example of a membrane power device 10 according to the present invention in which dry back-side etching is used to produce the membrane 16. The walls of the remaining portions of the substrate 11 are vertical as shown in Figure 32. Following the membrane formation by dry etching, a terminal layer 103 is applied to the membrane bottom surface 17 to form one of the main terminals of the device 10. As previously explained the dry etch has the advantage that the volume occupied by the gap in the substrate 11 is no longer dependent on the thickness of the substrate 11 and therefore the area of the membrane 16 is easier to control.

Figure 33 shows a cross-section of the device 10 shown in Figure 31. In this example, a termination region 106 of the device 10 is placed outside the membrane 16 whilst the active region 18 is placed within the membrane 16. The termination region 106 is used in power devices to suppress premature breakdown at the edge of the device 10 while the device blocks the voltage between the main terminals. The termination region 106 does not play an active role in the on-state and hence substantially no current conduction takes place in the termination region 106 during on-state operation. To minimise the on-state resistance and power losses, it is desirable that the drift layer 20 is as thin as possible. However, to support a higher breakdown at the device edge and thus force actual breakdown to occur in the active region, the termination region 106 is preferred to be thicker. For this reason, the active region 18 is placed inside the membrane 16 region whilst preferably the termination region 106 lies outside the membrane 16 on a thicker layer than the membrane 16. The termination 106 in this example benefits from having a substrate 11 underneath

-43-

which facilitates the spreading of the depletion region in a wider volume while the device 10 blocks the high voltage across the main terminals. The termination region 106 and the substrate 11 may have a different doping than the drift layer 20 placed within the active region 18. In a preferred embodiment, the substrate 11 is more lowly doped than the drift region 20. The termination region 106 can be in the form of highly doped floating rings (known per se) encircling the active region 18 of the device 10 which help to spread the depletion region on a larger area at the surface, each pair of rings withstanding in the space between them a fraction of the total voltage, thereby reducing the risk of edge premature breakdown. This termination, known as floating ring termination, may comprise field plates and channel/depletion stoppers. Alternatively, the termination may be in the known form of junction termination extension (JTE) or field plate termination.

Figure 34 shows in detail an example of a membrane vertical power MOSFET according to the present invention in which the active region 18 contains a drift region 20 of n conductivity type placed within the membrane 16 with a termination region 106 placed outside the membrane region 16. In this example, the termination region 106 is made of several concentric floating highly doped p-type rings 107 and a final highly doped n-type depletion stopper ring 108. The power MOSFET has highly doped n-type source 109 and drain 122 regions, an insulated gate formed by an insulating layer 121 and a polysilicon/metal layer 105 which acts as a control terminal. The source terminal 104 is placed on the top surface 15 and the drain terminal 103 is attached to the membrane bottom surface 17. The source

-44-

terminal 104 contacts both the source region 109 and the p well 120. The drain terminal 103 contacts the highly doped n-type drain region 122. The operation of the MOSFET in the on-state relies on the formation of an inversion layer at the surface of the p well 120 when a gate voltage is applied to the control terminal 105. In this mode, electrons are transported from the source region 109 via the said inversion layer formed in the p well 120 through the drift region 20 to the drain region 122. To minimise the on-state resistance, it is preferred that the drift region 20 is thin and relatively more highly doped compared to the substrate 11. During the off-state, when a high voltage is applied across the main terminals 103,104, the drift region 20 is completely depleted of mobile carriers and supports the largest fraction of the voltage in the active area. The potential lines in the drift region 20 are parallel to the top surface 15 and the membrane bottom surface 17 and ideally uniformly distributed inside the drift layer 20. In the termination region 106, the depletion region has more room to spread inside the substrate 11, thereby avoiding crowding of potential lines and premature breakdown at the edge of the drift region. The substrate 11 may be more lowly doped than the surface of the termination region 106 and the drift region 20. It should be noted that there is substantially no on-state current conduction in the termination region 106 and therefore the thick and relatively lowly doped substrate 11 does not affect adversely the on-state resistance and does not add additional power losses as would have been otherwise expected if the substrate 11 had been present under the membrane 16. It will be understood that for simplicity, the internal structure of the MOSFET is only shown in two dimensions in Figure 34.

-45-

Figure 35 shows a schematic perspective view of a 3D membrane power device 10 with a terminal 103 placed on the bottom 17 of the membrane 16. The drift region of the 3D
5 membrane power device is comprised of several pairs of n, p regions 110,111 disposed in the x,z plane such that they form transverse junctions in the z direction. If the regions 110,111 are thinner in the z direction than in the y direction, the drift region 20 depletes faster in the z
10 direction than in the y direction when a high voltage is applied across the main bottom terminal 103 and a top main terminal (not shown) placed on the top surface 15. This ensures higher breakdown ability and that the potential lines are parallel to the top surface 15 and the bottom
15 surface 17 and substantially uniformly distributed across the drift region.

Figures 36a to 36c show schematically an example of a method of fabricating a device 10 according to the present
20 invention. In this example, the thin layer 13 comprises a semiconductor layer 14 under which is provided a buried insulating oxide layer 50 under which is provided the substrate 11. As in the examples described above (for example with reference to Figure 9), the semiconductor
25 substrate 11 below the buried insulating layer 50 is partially removed by back-side etching with the buried insulating layer 50 acting as an etch-stop to form the membrane 16, as shown in Figure 36a. In this example, as indicated in Figure 36b, the portion of the buried
30 insulating layer 50 below the membrane portion of the semiconductor layer 14 is also then removed so that the exposed bottom surface of the semiconductor layer 14 provides the bottom surface 17 of the membrane 16. This

-46-

removal of the buried insulating layer 50 in the region of the membrane 16 allows a terminal layer 103 to be deposited on the back-side of the device. As shown, in this example, the bottom terminal layer 103 extends over the whole of the bottom surface 17 of the membrane 16 and down the inwardly facing sidewalls and under the bottom surfaces of the remaining leg portions of the substrate 11.

Figures 37 to 40 show schematically examples of a membrane power device 10 with a terminal attached to the membrane bottom surface in an integrated circuit containing low voltage/low power devices and circuits and other power devices.

Figure 37 shows for example four membrane power devices each featuring independent terminals with four main terminals 103 attached to the bottom of the membrane, and four main terminals 104 placed on the top of the membrane. Independent control terminals 105 can be used to control the operation of each individual power device. The power devices placed on the membrane 16 are isolated from each other through isolation layers 19 as described in previous examples.

Figure 38a shows a schematic cross-section of a power integrated circuit 40 which contains one membrane power device 10 with a main terminal 103 applied to the bottom surface and low power CMOS and bipolar devices 41 placed outside the membrane 16. Alternatively, the CMOS and bipolar devices 41 can also be placed within the membrane 16 as shown in Figure 38b or on a separate membrane 16 formed over the same original substrate 11 as shown in Figure 38c. Preferably the bottom terminal 103 does not extend under the low power devices and circuits. The

-47-

example of Figure 38d differs from that of Figure 38c in that the isolation layers 19 are placed outside the membranes 16.

5 The structures shown schematically in Figures 39a to 39d are SOI correspondents to those shown in Figures 38a to 38d. In these examples, the insulating layer 50 is used as an etch stop to form the membrane 16. The insulating layer 50 also helps to isolate individual devices placed within
10 the thin layer 13 from the substrate 11.

Figures 40a to 40d show schematically possible ways to integrate more than one membrane power device with independent main bottom terminals 103 in the same power
15 integrated circuit 40. In the example of Figure 40a, two power devices 10a and 10b each having a respective bottom main terminal 103a, 103b are integrated on the same membrane 16. In the example of Figure 40b, an insulating layer 50 is used to form the membrane 16 and help isolation of
20 individual devices within the power integrated circuit 40. The example of Figure 40c differs from that of Figure 40b in that the outer isolation layers 19 are placed outside the membrane 16. The inner isolation layer 19 in the example of Figure 40c which separates the first power
25 device 10a from the second power device 10b remains within the membrane 16 as also shown in the example of Figure 40b. In the example of Figure 40d, the membrane power devices 10a, 10b having independent bottom terminals 103a, 103b respectively are placed on different membranes 16a, 16b
30 respectively formed above the same original substrate 11. To isolate the membrane power devices from each other, a further membrane 16c which may contain one isolation layer

-48-

19 is formed above the original substrate 11 and placed between the adjacent membrane power devices 10a,10b.

Figures 41a to 41c show in more detail examples of a
5 membrane vertical power MOSFET. Figure 41a shows a
membrane vertical power MOSFET according to an embodiment
of the present invention using the known DMOS technology.
The power MOSFET has highly doped n-type source 109 and
drain 122 regions, an insulated gate formed by an
10 insulating layer 121 and a polysilicon/metal layer 105
which acts as a control terminal. The source terminal 104
is placed on the top surface 15 and the drain terminal 103
is attached to the membrane bottom surface 17. The source
terminal 104 contacts both the source region 109 and the p
15 well 120. The drain terminal 103 contacts the highly doped
n-type drain region 122. The operation of the MOSFET in
the on-state relies on the formation of an inversion layer
at the surface of the p well 120 when a gate voltage is
applied on the control terminal 105. In this mode,
20 electrons are transported from the source region 109 via
the said inversion layer formed in the p well 120 through
the drift region 20 to the drain region 122. During the
off-state, when a high voltage is applied across the main
terminals 103,104, the drift region 20 is completely
25 depleted of mobile carriers and supports the largest
fraction of the voltage in the active area. The potential
lines in the drift region 20 are parallel to the top
surface 16 and the membrane bottom surface 17 and ideally
uniformly distributed inside the drift layer 20. The
30 highly doped n-type drain layer 122 may be a buried layer
formed prior to the back-side etch which defines the
membrane 16. In this way, the n-type layer 122 may be used
as an indirect means to stop the back-etch using a known

-49-

electrochemical technique. To facilitate the electrochemical etch, the substrate 11 may be of p-type doping to form a junction with the said n-type layer 122.

5 The example of Figure 41b differs from the example of Figure 41a in that the highly doped n-type drain layer 122 is formed by masked or blank back-side deposition after the membrane 16 is formed. The drain terminal 103 is applied to the membrane bottom surface 17 after the membrane 16 is
10 formed and the n-type drain layer 122 is introduced in the membrane 16 from the back-side of the device.

Figure 41c shows an example of a membrane vertical power MOSFET according to an embodiment of the present
15 invention using trench technology. The structure in Figure 41c differs from that shown in Figure 41b in the way the insulated gate is formed at the top of the structure. In the structure of Figure 41c, the inversion layer in the 120 is formed vertically, substantially perpendicular to the
20 top surface 15. This structure has the advantage of enhanced channel density and higher packing density.

Figures 42a to 42c show in detail examples of vertical Insulated Gate Bipolar Transistors (IGBT) membrane power
25 devices in which bipolar conduction within the drift region 20 suspended on the membrane 16 is employed and which generally correspond to the membrane vertical power MOSFETs shown in Figures 41a to 41c. The main difference in the IGBTs is the use of a highly doped p-type hole injector
30 anode layer 123 in contact with the anode terminal 103. Bipolar conduction of the current is substantially perpendicular to the top surface 15 and is characterised by conductivity modulation in the drift layer 20 to reduce the on-state voltage drop across the drift layer 20. The

-50-

n-type buffer layer 122 and the p-type anode layer 123 may be formed prior to the formation of the membrane 16 as shown in Figure 42a or after the formation of the membrane 16 as shown in Figure 42b. Figure 42c shows a trench
5 variant of the membrane IGBT shown in Figure 42b. In Figure 42a, the anode layer 123 may be used directly or indirectly as an etch-stop to form the membrane 16.

Figure 43a and b show examples of a power integrated
10 circuit containing two vertical power MOSFETs 10a,10b using trench technology and suspended on separate membranes 16a,16b. In the example of Figure 43a, the devices 10a,10b feature independent terminals and are isolated from each other through the use of a third membrane 16c and an
15 isolation layer 19. The three membranes 16a,16b,16c are formed in the same step and in this example by use of a back-side dry etch which results in vertical walls for the remaining leg portions of the substrate 11 which, as previously described, are advantageous for obtaining a
20 better control of the membrane area and integrating a large number of devices within the same chip. The example of Figure 43b is a SOI variant of the example of Figure 43a. The isolation layer 19 in this case is placed outside the membranes 16a and 16b and together with the buried
25 dielectric layer 50 ensures an effective isolation of the two power devices 10a,10b from each other. The examples in Figures 43a and 43b show two membrane power MOSFETs integrated in the same chip, but any other membrane power devices can be used in a similar way and isolated from each
30 other as shown in this figure.

Although the above examples refer primarily to silicon, the power membrane devices of the present

-51-

invention can be built on other semiconductors, such as for example silicon carbide (SiC), diamond, GaAs, GaN or other III-V materials.

- 5 The drift region as part of the first thin layer 13 can be made of wide band gap materials, such as diamond, GaAs, GaN and SiC or can be made of heterojunctions such as GaN and AlGaN combinations or other suitable materials.
- 10 The insulating layer 50 is described primarily with reference to silicon dioxide but other insulating or semi-insulating materials, such as diamond, nitride or combinations of nitride and oxide, can be used.
- 15 The heat sink layer 45 can be made of diamond, aluminium nitride, boron nitride or other materials with good electrically insulating properties and high thermal conductivity.
- 20 Some examples of the thickness of the membrane 16 have already been given above. Generally, in a lateral device, the membrane 16 may have a thickness in the range 0.1 μ m to 10 μ m or 20 μ m or so. Generally, in a vertical device, the membrane 16 may have a thickness in the range 6 μ m or 10 μ m
- 25 to 60 μ m or 100 μ m or 180 μ m or so.

Embodiments of the present invention have been described with particular reference to the examples illustrated. However, it will be appreciated that

30 variations and modifications may be made to the examples described within the scope of the present invention.

-52-

CLAIMS

1. A power semiconductor device having an active region that includes a drift region, at least a portion of the drift region being provided in a membrane having opposed top and bottom surfaces, the top surface of the membrane having electrical terminals connected directly or indirectly thereto to allow a voltage to be applied laterally across the drift region, the bottom surface of the membrane not having a semiconductor substrate positioned adjacent thereto.
2. A power semiconductor device having an active region that includes a drift region provided in a layer, the layer being provided on a semiconductor substrate, at least a portion of the semiconductor substrate below at least a portion of the drift region being removed such that said at least a portion of the drift region is provided in a membrane defined by that portion of the layer below which the semiconductor substrate has been removed, the top surface of the membrane having electrical terminals connected directly or indirectly thereto to allow a voltage to be applied laterally across the drift region.
3. A power semiconductor device having an active region that includes a drift region, at least a portion of the drift region being provided in a membrane having opposed top and bottom surfaces, at least one electrical terminal connected directly or indirectly to the top surface and at least one electrical terminal connected directly or indirectly to the bottom surface to allow a voltage to be applied vertically across the drift region, the bottom

-53-

surface of the membrane not having a semiconductor substrate positioned adjacent thereto.

4. A power semiconductor device having an active region
5 that includes a drift region provided in a layer, the layer
being provided on a semiconductor substrate, at least a
portion of the semiconductor substrate below at least a
portion of the drift region being removed such that said at
least a portion of the drift region is provided in a
10 membrane defined by that portion of the layer below which
the semiconductor substrate has been removed, and at least
one electrical terminal connected directly or indirectly to
the top surface and at least one electrical terminal
connected directly or indirectly to the bottom surface to
15 allow a voltage to be applied vertically across the drift
region.

5. A device according to any of claims 1 to 4, wherein
only part of the drift region is provided in the membrane.
20

6. A device according to any of claims 1 to 4, wherein
the whole of the drift region is provided in the membrane.

7. A device according to any of claims 1 to 6, comprising
25 at least one isolation layer surrounding the drift region.

8. A device according to claim 7, wherein the at least
one isolation layer is provided in said membrane or in a
separate membrane to extend from the top surface of the
30 membrane to the bottom surface of the membrane.

-54-

9. A device according to any of claims 1 to 8, comprising at least one isolation layer surrounding the drift region and provided outside the membrane.
- 5 10. A device according to any of claims 7 to 9, wherein the or at least one isolation layer is provided by electrically insulating material.
11. A device according to any of claims 7 to 10, wherein
10 the or at least one isolation layer is provided by a highly doped semiconductor layer which in use is biased to provide a junction that is reverse-biased or biased below the forward-bias level.
- 15 12. A device according to any of claims 1 to 11, and further comprising at least one additional power device having a drift region at least a portion of which is provided on said membrane or on a separate membrane.
- 20 13. A device according to any of claims 1 to 12, and further comprising at least one low voltage device.
14. A device according to claim 13, wherein said at least one low voltage device is provided in said membrane.
- 25 15. A device according to claim 13, wherein said at least one low voltage device is provided outside said membrane.
16. A device according to claim 15, wherein said at least
30 one low voltage device is provided in a further membrane.

-55-

17. A device according to any of claims 12 to 16, comprising at least one isolation layer, said isolation layer providing electrical isolation between adjacent devices.

5

18. A device according to claim 17, wherein the said isolation layer is placed on a further membrane.

19. A device according to claim 1 or claim 2 or any claim
10 when dependent thereon, comprising an electrically insulating and thermally conductive layer adjacent the bottom surface of the membrane.

20. A device according to claim 1 or claim 2 or any claim
15 when dependent thereon, wherein the membrane comprises a semiconductor layer provided on an electrically insulating layer.

21. A device according to claim 1 or claim 2 or any claim
20 when dependent thereon, comprising a mechanically strong and electrically insulating layer provided under the membrane.

22. A device according to any of claims 1 to 21, wherein
25 the drift region has a non-uniform doping profile.

23. A device according to claim 22, wherein the doping concentration of the drift region at a high voltage terminal side of the device is relatively high and the
30 doping concentration of the drift region at a low voltage terminal side of the device is relatively low.

-56-

24. A device according to claim 22 or claim 23, wherein the doping concentration of the drift region varies linearly from one side of the drift region to the other.

5 25. A device according to claim 1 or claim 2 or any claim when dependent thereon, wherein the drift region comprises at least two semiconductor layers of alternating conductivity type arranged one above the other and in contact with each other.

10

26. A device according to any of claims 1 to 24, wherein the drift region comprises a plurality of laterally adjacent semiconductor regions of alternating conductivity type.

15

27. A device according to any of claims 1 to 24, wherein the drift region comprises a plurality of laterally adjacent semiconductor cells of alternating conductivity type arrayed around the plane of the device.

20

28. A device according to any of claims 1 to 27, comprising a termination region adjacent to and in contact with the drift region, said termination region being provided to reduce the effect of premature breakdown at the
25 edge of the drift region.

29. A device according to claim 28, wherein at least a portion of the said termination region is placed inside the membrane.

30

30. A device according to claim 28, wherein at least a portion of the said termination region is placed outside the membrane.

31. A device according to any of claims 28 to 30, wherein the drift region is more highly doped than at least a portion of the termination region.

5

32. A device according to any of claims 28 to 31, wherein the drift region is more highly doped than the semiconductor substrate.

10 33. A method of forming a power semiconductor device having an active region that includes a drift region, the method comprising the steps of:

forming, in a layer provided on a semiconductor substrate, a power semiconductor device having an active
15 region that includes a drift region; and,
removing at least a portion of the semiconductor substrate below at least a portion of the drift region such that said at least a portion of the drift region is provided in a membrane defined by that portion of the layer
20 below which the semiconductor substrate has been removed.

34. A method according to claim 33, wherein said at least a portion of the semiconductor substrate is removed by wet etching.

25

35. A method according to claim 33, wherein said at least a portion of the semiconductor substrate is removed by dry etching.

30 36. A method according to claim 34 or claim 35, wherein said at least a portion of the semiconductor substrate is removed using a buried insulating layer as an etch stop.

-58-

37. A method according to any of claims 33 to 36, wherein
at least one semiconductor layer is introduced by
implantation, diffusion or deposition from the back-side of
5 the device following the formation of the membrane.

38. A method according to any of claims 33 to 37, wherein
a bottom terminal layer is applied to the bottom of the
membrane, said bottom terminal layer being in contact with
10 at least one semiconductor layer within the membrane.

39. A method according to any of claims 33 to 37,
comprising the step of applying an electrically insulating
and thermally conductive layer adjacent the bottom surface
15 of the membrane.

40. A method according to claim 39, wherein the
electrically insulating and thermally conductive layer is
applied by a deposition process.

20

1/42




Figure 1a






Figure 1b



2/42




Figure 2a




Figure 2b

3/42




Figure 3a




Figure 3b

4/42




Figure 4a




Figure 4b

5/42




Figure 5a




Figure 5b

6/42




Figure 6a




Figure 6b




Figure 6c




Figure 6d

7/42




Figure 7

8/42




Figure 8

9/42




Figure 9a




Figure 9b

10/42




Figure 10a




Figure 10b

11/42




Figure 11a




Figure 11b

12/42




Figure 12




Figure 13a




Figure 13b




Figure 13c




Figure 14a




Figure 14b




Figure 14c

15/42




Figure 15




Figure 16




Figure 17a




Figure 17b




Figure 17c

18/42




Figure 18a




Figure 18b




Figure 19

20/42




Figure 20




Figure 21

21/42




Figure 22a




Figure 22b

22/42




Figure 23a




Figure 23b




Figure 23c




Figure 24

24/42




Figure 25a




Figure 25b




Figure 25c

25/42




Figure 26a




Figure 26b

26/42




Figure 27a




Figure 27b

27/42




Figure 28a




Figure 28b

28/42




Figure 29a





Figure 29b



31/42




Figure 32




Figure 33




Figure 34

35/42




Figure 36a




Figure 36b




Figure 36c




Figure 37

37/42




Figure 38a




Figure 38b




Figure 38c




Figure 38d

38/42




Figure 39a




Figure 39b




Figure 39c




Figure 39d







Figure 40d

40/42




Figure 41a




Figure 41b




Figure 41c

41/42




Figure 42a




Figure 42b




Figure 42c

42/42




Figure 43a




Figure 43b



Creation date: 10-05-2003
Indexing Officer: TGEDAMU - TARIQUA GEDAMU
Team: OIPEScanning
Dossier: 10622094

Legal Date: 09-22-2003

No.	Doccode	Number of pages
1	FRPR	36

Total number of pages: 36

Remarks:

Order of re-scan issued on

